



HB-026S VIDEO PROJECTOR CEILING MOUNT FOR SIM 2 HT-500 LINK

The Chief HB-026S video projector ceiling mount is designed to provide fast, simple and secure installation of the SIM 2 HT-500 LINK. Special roll, pitch, yaw and horizontal adjustments simplify projection positioning for image alignment. The HB-026S mount also has positive registration lock so that the projector may be removed without losing projector mount registration.

WARNING: IMPROPER INSTALLATION MAY RESULT IN SERIOUS PERSONAL INJURY! All components must be securely fastened to each other and to the ceiling, **AND** the ceiling **MUST** be capable of supporting 5 times the total weight of the installation. If it cannot, the ceiling **MUST** be reinforced.

Unpack and check contents:

- | | | | |
|-----|--|-----|--------------------------------|
| (1) | Deluxe ceiling mount housing assembly. | (6) | M6 Washers, flat |
| (1) | SIM 2 mounting bracket | (6) | M6 x 10mm Screws, PH, Phillips |
| (4) | 5/16" Flange Nuts | | |

INSTALLATION INSTRUCTIONS

1. Turn your projector upside down.
2. Place the SIM 2 mounting bracket on the bottom of the projector so the hooks are facing the back and the six holes in the bracket line up with the six threaded inserts in the bottom of the projector.
3. Slide the (6) M6 washers on the (6) M6 x 10mm Screws and install them into the six threaded inserts in the projector. **Securely tighten all six mounting screws at this time.**
4. Be sure that the method of support you are using for the VCM ceiling mount is securely installed to the ceiling. If not, the ceiling must be reinforced. Improper installation may result in serious personal injury.
5. Attach the VCM housing to your method of support and tighten firmly so the VCM housing is square to the screen.

PRECAUTION: *Installing a ceiling mount requires the presence of two persons familiar with mechanical installations. A third assistant is recommended for hanging the projector if it weighs over 75 Lbs.*

6. With the help of your assistants, lift the projector and install it to the four studs extending from the mounting plate. Be sure the SIM 2 mounting plate is seated in slots. **Tighten securely** using the (4) 5/16" flange nuts.

For projector alignment see attached sheet.Error! No index entries found.